

Smart Power Sensor



Accurate

Class 1 measurement accuracy



Simple & Easy

LCD display, easy to set and check



Energy Efficient

Overall power consumption ≤ 1.5 W

Technical Specification	DTSU666-HW/YDS60-80
General Data	
Dimension (H x W x D)	100 x 72 x 80 mm (3.9 x 2.8 x 3.1 inch)
Mounting type	DIN35 Rail
Weight (including cables)	< 0.5 kg
Power Supply	
Power grid type	3P4W/3P3W
Input voltage (line voltage)	90 ~ 500 Vac
Power consumption	≤ 1.5 W
Measurement Range	
Line voltage	90 Vac ~ 1000 Vac (> 500 with external PT ¹)
Phase voltage	52~577 Vac
Current	0 ~ 80 A(>80 with external CTs ²)
Measurement Accuracy	
Voltage / Current	± 0.5 %
Power / Energy	± 1 %
Frequency	± 0.01 Hz
Communication	
Interface	RS485
Baud rate	4800/9600/19200/115200 (Default 9600bps)
Communication protocol	Modbus-RTU
Environment	
Operating temperature range	-25 °C ~ 60 °C
Storage temperature range	-40 °C ~ 70 °C
Operating humidity	5 %RH ~ 95 %RH (non-condensing)
Others	
Accessories	RS485 Cable (10 m / 33 ft.)

*1 2nd voltage of CT should be 100V. And accuracy should be better than Class 0.5
 *2 2nd current of CT should be 1A or 5A. And accuracy should be better than Class 0.5